

**Quincy K-8 School
Changes to Drawings & Specs
Allstate Construction, Inc.
10-17-2025**

Drawings

A-115

1. Add tag for Door No. C175B (A-115).

A-601

2. At Door No. A100, change hardware set to 15.1 (A-601).
3. At Door No. A137, change hardware set to 15.0 (A-601).
4. At Door No. A143, change hardware set to 32.0 (A-601).
5. At Door No. A155A, change hardware set to 2.0 (A-601).
6. At Door No. A155B, change hardware set to 5.1 (A-601).
7. At Door No. A195, change hardware set to 12.0 (A-601).
8. At Door No. A195A, change door material to hollow metal (A-601).
 - At Door No. A195A, change hardware set to 19.1 (A-601).
9. At Door No. A195C, change door material to hollow metal (A-601).
 - At Door No. A195C, change hardware set to 19.1 (A-601).
10. At Door No. A195B, change hardware set to 22.1 (A-601).
11. At Door No. A195D, change hardware set to 1.0 (A-601).
12. At Door No. A196B, change door material to hollow metal (A-601).
 - At Door No. A196B, change hardware set to 21.1 (A-601).
13. At Door No. A198, change hardware set to 1.1 (A-601).
14. At Door No. B128C, change hardware set to 56.0 (A-601).
15. At Door No. B171A, add hardware set 17.0 (A-601).
16. At Door No. B172, add hardware set 17.0 (A-601).
17. At Door No. B173A, add hardware set 17.0 (A-601).
18. At Door No. B174C, change hardware set to 1.0 (A-601).
19. At Door No. B176B, add hardware set 19.0 (A-601).
20. At Door No. B177, add hardware set 17.0 (A-601).

A-602

21. At Door No. C175B, add hardware set 19.0 (A-602).
22. At Door No. C176B, add hardware set 19.0 (A-602).
23. At Door No. A207B, add hardware set 27.0 (A-602).
24. At Door No. B271, add hardware set 17.0 (A-602).
25. At Door No. B272, add hardware set 17.0 (A-602).
26. At Door No. B275, add hardware set 17.0 (A-602).
27. At Door No. B276, add hardware set 21.0 (A-602).
28. At Door No. B277, add hardware set 19.0 (A-602).
29. At Door No. C270, add hardware set 17.0 (A-602).
30. At Door No. C275, add hardware set 21.0 (A-602).
31. At Door No. C276, add hardware set 19.0 (A-602).

AG-601

- 32. At Door No. D014, add hardware set 32.0 (AG-601).
- 33. At Door No. D109, change hardware set to 27.0 (AG-601).
- 34. At Door No. D109, change hardware set to 27.0 (AG-601).
- 35. At Door No. D120, add hardware set 57.0 (AG-601).
- 36. At Door No. D125, add hardware set 57.0 (AG-601).
- 37. At Door No. D131, change hardware set to 57.0 (AG-601).
- 38. At Door No. D149, change hardware set to 57.0 (AG-601).

AS-601

- 39. At Door No. F101, add hardware set 8.1 (AS-601).

Specifications

080671 Door Hardware Schedule

- 40. At hardware set 7.0, omit Door No. A148D (080671).
 - At hardware set 48.0, add Door No. A148D (080671).
- 41. At hardware set 19.0, add Door No. A149 (080671).
 - At hardware set 19.1, omit Door No. A149 (080671).
- 42. Door B174B is single (A-114) instead of pair (hardware set 1.0/080671).
- 43. Door B174C is single (A-114) instead of pair (hardware set 1.0/080671).
- 44. At hardware set 52.0, add Door No. A176 (080671).
 - At hardware set 53.0, omit Door No. A176 (080671).
- 45. At hardware set 43.0, omit Door No. B137 (080671).
 - At hardware set 45.0, add Door No. B137 (080671).
- 46. At hardware set 1.0, add Door No. D118 (080671).
- 47. At hardware set 1.0, add Door No. D119 (080671).